




# Dell Inspiron 10z 1120 Hard Drive Replacement

Written By: Terrence15



---

## INTRODUCTION


In this guide, we will show you how to remove and replace the Hard Drive.



### TOOLS:

- [Phillips #0 Screwdriver](#) (1)
-

## Step 1 — Remove the Screws




**⚠ WARNING:** Before working inside your computer, read the safety information that shipped with your computer. Follow the instructions in [Before You Begin](#).

**⚠ CAUTION:** To avoid electrostatic discharge, ground yourself by using a wrist grounding strap or by periodically touching an unpainted metal surface (such as a connector on your computer).


- Remove the two screws that secure the hard-drive assembly to the computer base.

## Step 2 — Sliding the Hard Drive




- Using the pull-tab, slide the hard-drive assembly to the side to disconnect it from the connector on the system board.

### Step 3 — Lifting the Hard-drive




- Lift the hard-drive assembly out of the computer base.

### Step 4 — Remove the Screws



- Remove the four screws that secure the hard-drive bracket to the hard drive.

## Step 5 — Lifting the Hard-Drive



- Lift the hard-drive bracket off the hard drive.


## Step 6 — Placing the Hard Drive



- Place the hard drive in the hard-drive bracket.




## Step 7 — Replace the Screws




- Replace the four screws that secure the hard-drive bracket to the hard drive.

## Step 8 — Placing the Hard Drive



- Place the hard-drive assembly in the computer base.

## Step 9 — Replace the Two Screws



- Replace the two screws that secure the hard-drive assembly to the computer base.

To reassemble your device, follow these instructions in reverse order.